



- NOTES :**
- THE FOLLOWING INFORMATION IS OBTAINED FROM THE PROJECT DESIGN DRAWINGS :
 - POLE LENGTH AND STRENGTH.
 - SPECIAL FOUNDATION REQUIREMENTS.
 - POLE EMBEDMENT DEPTH.
 - PHASE CONDUCTOR AND OVERHEAD EARTHWIRE SIZE.
 - VARIATIONS TO STANDARRD CROSSARM REQUIREMENTS.
 - STAY REQUIREMENTS.
 - DEVIATION ANGLE.
 - ASSESSED EARTHING REQUIREMENTS.
 - THE MAXIMUM LINE DEVIATION ANGLE TO BE CONSTRUCTED ON THIS ARRANGEMENT IS TO BE DETERMINED BY THE LINE DESIGNER.
 - WHEN DESIGNING UNDERBUILT CIRCUITS ON A 33kV STRUCTURE, THE POSSIBLE USE OF LIVE LINE WORKING PROCEDURES MUST BE CONSIDERED WHEN NOMINATING THE CIRCUIT SEPARATION TO ALLOW A MINIMUM CLEARANCE OF 2500mm IF REQUIRED.
 - THE LOAD AND DEVIATION ALLOWABLE ON THE EYEBOLT IS TO BE DETERMINED FROM DRG: 520324.
 - LONGROD INSULATORS TO BE USED UNDER NORMAL CONDITIONS.
 - THE LOAD AND DEVIATION ALLOWABLE ON THE EYEBOLT AND EYENUT ASSEMBLY IS TO BE DETERMINED FROM DRG: 520331.
 - STAYS TO BE INSTALLED SO THAT THE STAY WIRE CLEARANCE FROM THE PHASE CONDUCTORS COMPLIES WITH THE STATUTORY REQUIREMENTS.
 - EYEBOLTS ARE TO BE INSTALLED IN THE DIRECTION OF THE OVERHEAD CONDUCTORS
 - NON TENSION COMPRESSION JOINTS TO BE USED WHEN REQUIRED TO JOIN THROUGH CONDUCTORS.
 - USE THE ANGLE TYPE CONDUCTOR TIE ARRANGEMENT AS SHOWN ON DRG: 514038.
 - CONDUCTOR TO POLE CLEARANCE IS TO BE A MINIMUM OF 380mm.
 - INSTALL A 33/920 PIN INSULATOR ARRANGEMENT TO HOLD THE CONDUCTOR TAPPING TO INCREASE THE CONDUCTOR CLEARANCE TO THE STEEL CROSSARM AND REDUCE THE RISK OF A FLASHOVER DUE TO PERCHED BIRDS.
 - THE CROSSARM BRACE ATTACHMENT POINT ON A CONCRETE POLE IS TO BE AN M12 STAINLESS STEEL EARTH FERRULE.
 - THE OHEW IS TO BE BONDED TO AN M12 STAINLESS STEEL EARTH FERRULE ON THE CONCRETE POLE.
 - ONLY THE 3000mm STEEL CROSSARM OPTION IS SHOWN ON THIS CONSTRUCTION DRAWING. REFER TO DRG: 237491 FOR DRILLING PATTERN OF ALTERNATE CROSSARM.
 - ONLY THE SINGLE PHASE CONDUCTOR WITH OPGW THROUGH TERMINATION AND OPGW TEE OFF TERMINATION OVERHEAD EARTHWIRE OPTION IS SHOWN ON THIS CONSTRUCTION DRAWING.
 - USE THE OPGW THROUGH TEE OFF TERMINATION ARRANGEMENT WHEN ERECTING AN UNBROKEN AND A BROKEN OPGW OVERHEAD EARTHWIRE. USE THE OPGW TEE OFF SPLICE BOX TERMINATION ARRANGEMENT WHEN BREAKING ALL OPGW OVERHEAD EARTHWIRES. USE THE STANDARD EARTHWIRE TEE OFF TERMINATION ARRANGEMENT WHEN ERECTING A NON OPGW OVERHEAD EARTHWIRE.
 - POLE STEPS SHOULD ONLY BE INSTALLED ON POLES WHERE ACCESS FOR NORMAL MAINTENANCE VEHICLES CANNOT BE MAINTAINED FOR THE LIFE OF THE POLE. IF POLE STEPS ARE INSTALLED, THEY ARE TO COMPLY WITH THE REQUIREMENTS OF NETWORK STANDARD NS128.
 - REFER TO DESIGNER SAFETY REPORT D22/272990 FOR ATYPICAL HAZARDS ASSOCIATED WITH THIS STANDARD CONSTRUCTION.

| | | | |
|----|---|--------|-----|
| 13 | STEP - POLE (SEE NOTE 18) | 514084 | A/R |
| 12 | OPGW - SPLICE BOX & COILED CABLE BRACKET, CONDUCTOR, MOUNTING ARRANGEMENT (USE WITH OPGW OHEW OPTIONS ONLY) | 565743 | 1 |
| 11 | EARTHWIRE - TERMINATION, TEE OFF, OVERHEAD, MOUNTING, ARRANGEMENT -2 (SEE NOTES 14, 16 & 17) | 514147 | 1 |
| | OPGW - TERMINATION, TEE OFF, CONDUCTOR, MOUNTING, ARRANGEMENT -2B (SEE NOTES 14, 16 & 17) | 251960 | |
| 10 | OPGW - TERMINATION, TEE OFF, CONDUCTOR, MOUNTING, ARRANGEMENT -2A (SEE NOTES 14, 16 & 17) | 251960 | 6 |
| | JOINT - COMPRESSION, NON TENSION (TO SUIT DUAL CONDUCTORS) (SEE NOTES 9 & 16) | 514053 | |
| 9 | JOINT - COMPRESSION, NON TENSION (TO SUIT CONDUCTOR) (SEE NOTES 9 & 16) | 514053 | 3 |
| | CLAMP - PARALLEL GROOVE, 3 BOLT (TO SUIT DUAL CONDUCTORS) (SEE NOTE 16) | 514099 | |
| 8 | CLAMP - PARALLEL GROOVE, 3 BOLT (TO SUIT SINGLE CONDUCTOR) SEE NOTE 16) | 514099 | 3 |
| | INSULATOR - LONGROD, 33kV, DUAL CONDUCTOR, POLYMERIC STRING, ARRANGEMENT -2 (SEE NOTES 5 & 16) | 250120 | |
| 7 | INSULATOR - LONGROD, 33kV, POLYMERIC STRING, ARRANGEMENT -2 (SEE NOTES 5 & 16) | 158754 | 9 |
| | CROSSARM - MOUNTING ARRANGEMENT 2a (GALVANISED STEEL OR COMPOSITE FIBRE CROSSARM) (SEE NOTES 13 & 15) | 514176 | |
| 6 | TIE - CONDUCTOR, HIGH VOLTAGE, SUPPORT ARRANGEMENT (SEE NOTE 10) | 514038 | 2m |
| 5 | INSULATOR - 33kV, AERODYNAMIC, (33/920) AND PIN ARRANGEMENT (SEE NOTE 12) | 514006 | 2 |
| 4 | CROSSARM - MOUNTING ARRANGEMENT 3a (GALVANISED STEEL OR COMPOSITE FIBRE CROSSARM) (SEE NOTES 13 & 15) | 514176 | 1 |
| 3 | FOOTING - CONCRETE POLE, ARRANGEMENT (SEE NOTE 1) | 512331 | 1 |
| 2 | EARTHING - CONCRETE/STEEL, SINGLE POLE, BUTT, ARRANGEMENT | 520209 | 1 |
| 1 | POLE - CONCRETE (AS REQUIRED) | | 1 |

ALL DIMENSIONS IN MILLIMETRES UNLESS NOTED OTHERWISE. DO NOT SCALE.

| | | | | | | | | | |
|--|---|---|--|--|--|--|--|------------------------------|------------------|
| CAD DRAWING DO NOT MANUALLY AMEND AMENDMENTS DWN: GARY HUGHES CHKD: GARRY CRAIG DATE: 14/10/2013 AUSGRID BORDER APPLIED. | APPD by: GLENN FORD DWN: P.R. CHKD: P.J. APP'D: G.F. | DATE: 08/11/2022 MULTIPLE CROSSARM OPTION & FOUNDATION DETAILS ADDED. NOTES & MATERIAL LIST AMENDED. DUAL CONDUCTOR & OHEW OPTIONS ADDED. | COMPOSITE FIBRE CROSSARMS SPECIFICATION 237491 | | NETWORK STANDARD 145 NEWCASTLE RD WALLSEND, NSW 2287 | SCALE 1:25 DESIGNED - DRAWN P.RIOS CHECKED PHIL JONES APPROVED STEPHEN CONNOR DATE 20/12/2007 | STANDARD CONSTRUCTION 33kV THROUGHY TERMINATION TEE OFF CONSTRUCTION WITH OVERHEAD EARTHWIRE 4-17C/E | SIZE A2 DRAWING No 174244 | SHEET 1 AMD 2 |
| | | | HV CONDUCTOR TIE SUPPORT ARRANGEMENTS 514038 20mm EYEBOLT & EYENUT ASSEMBLY LOADING AND DEVIATION GRAPH 520331 20mm EYEBOLT LOADING AND DEVIATION GRAPH 520324 | | | | | | |